

# 1250 Rocker Switches 10A 250Vac



10(6)A 250Vac T100  
6A 400Vac T100  
1A 30Vdc



UL CSA 10A 250Vac  
UL CSA 16A 250Vac Resistive  
UL CSA 125Vac 1/2hp  
UL CSA 1A 30Vdc  
UL 100°C, file E45221, CSA file LR10990

*In house test*

Inrush 75A to EN61058-1 & 10A 28Vdc



RoHS compliant

3mm contact gap  
Technical data on pages 4 & 5

- ▶ Standard rocker switch
- ▶ Double pole in single pole body
- ▶ Snap in or sub panel mount
- ▶ Integral terminal barrier
- ▶ Push on or PCB terminals
- ▶ High inrush tolerance
- ▶ Bezel size:  
29.5 x 15mm (snap in)  
23.5 x 13mm (sub panel mount)



C1250AP - - -



C1250AN - - -

**C 1250 A P - - -**

TERMINAL FUNCTION ROCKER BODY PRINT, COLOUR, ETC

▶ TERMINAL	▶ FUNCTION	▶ ROCKER	▶ BODY	▶ OPTIONS
<p><b>C</b></p> <p>6.3 x 0.8</p>	<p>On when pressed over terminal 1</p> <p><b>1250</b></p> <p>ON - OFF Double pole</p> <p>Poles are 9.0mm between centres.</p>	<p><b>A</b> Curved</p> <p>Shown in N body</p>	<p><b>N</b></p> <p>Panel cut-out      Bezel</p> <p>Sub-panel      Facia</p> <p>Panel thickness      Dim X</p> <p>0.75-1.24      26.1/26.2</p> <p>1.25-1.99      26.3/26.4</p> <p>2.00-3.00      26.7/26.8</p>	<p><b>Finish</b> Matt finish only.</p> <p><b>Colour</b> Call factory for custom colours. A full range is available for large orders.</p> <p><b>Legend printing</b> Select from the examples or call factory for custom legends.</p>
<p><b>X</b></p> <p>PCB 0.8sq (N body only)</p>	<p>On when pressed over terminal 1</p> <p><b>1250SP</b></p> <p>ON - OFF Single pole</p>	<p><b>P</b></p> <p>Shown in P body</p>	<p><b>P</b></p> <p>Panel cut-out      Bezel</p> <p>Panel thickness</p> <p>0.75-3.00</p>	




Cut-outs must be punched in the direction of insertion

## Dimensions (mm)

**1250AN** (C terminals shown)

**1250AN** (X terminals shown)

**1250AP** (C terminals shown)



## Examples of printing



CL085



CL086